


Official**IN THE CLAIMS**

Claims 7 and 14 have been amended as set forth below.

1. (Previously Amended) A method of synchronizing the frequency of a local clock of a digital data decoder with the frequency of a program clock, wherein the decoder includes hardware for adjusting the local clock frequency and a processor having a software program for adjusting the local clock frequency, the method comprising the steps of: determining the difference between the local and program clock frequencies, then adjusting the frequency at which the local clock oscillates so that said difference approaches zero; including the steps of:

FI
i) using the hardware to adjust the local clock frequency until a threshold condition occurs, and
after the threshold condition occurs, using the processor to adjust the local clock frequency.

2. (Previously Amended) A method according to Claim 1, wherein the local clock oscillates at the local clock frequency, the method further comprising the steps of:

maintaining a local clock value based on the oscillations of the local clock;
receiving clock time stamps at the decoder which specify the program clock
signals and the frequency of the program clock;
maintaining a program clock value based on the program clock signals
received at the decoder;

determining if there is an absolute difference between the local clock value and the program clock value;

if there is an absolute difference between the local clock value and the program clock value, then adjusting the frequency at which the local clock oscillates so that said absolute difference approaches zero.

3. (Previously Amended) A method of synchronizing the frequency of a local clock of a digital data decoder with the frequency of a program clock, wherein the local clock oscillates at a local clock frequency, the method comprising the steps of:

determining the difference between the local and program clock frequencies, then adjusting the frequency at which the local clock oscillates so that said difference approaches zero;

maintaining a local clock value based on the oscillations of the local clock;

receiving clock time stamps at the decoder which specify program clock signals and the program clock frequency;

maintaining a program clock value based on the program clock signals received at the decoder;

determining if there is an absolute difference between the local clock value and the program clock value;

if there is an absolute difference between the local clock value and the program clock value, then adjusting the frequency at which the local clock oscillates so that said absolute difference approaches zero;

wherein the decoder includes hardware for adjusting the local clock frequency and a processor having a software program for adjusting the local clock frequency, and wherein the step of adjusting the frequency of the local clock includes the steps of:

using the hardware to adjust the local clock frequency until a threshold condition occurs; and

after the threshold condition occurs, using the processor to adjust the local clock frequency.

4. (Original) A method according to Claim 3, wherein the threshold condition is a function of the difference between the local clock value and the program clock value.

FI
OCC-1
5. (Original) A method according to Claim 3, wherein the step of using the processor to adjust the local clock frequency includes the steps of:

monitoring for the occurrence of the threshold condition; and

transmitting a signal to the processor when the threshold condition occurs.

6. (Cancelled)

7. (Currently Amended) A system for adjusting a local clock on a digital data decoder, wherein the clock oscillates at a local clock frequency, the system comprising:

means for maintaining a local clock value based on the oscillations of the local clock;

means for receiving clock signals transmitted to the decoder at that specify a program clock frequency;

means for maintaining a program clock value based on the clock signals transmitted to the decoder;

means for determining if there is any difference between the local clock and the program clock frequencies;

means for determining if there is an absolute difference between the local clock value and the program clock value; and

F1
OODL
means for adjusting the frequency at which the local clock oscillates, when there is a difference between the local clock and the program clock frequencies or an absolute difference between the local clock value and the program clock value, so that said difference approaches zero;

wherein the means for adjusting the frequency at which the local clock oscillates includes:

hardware for adjusting the local clock frequency until a threshold condition occurs; and

a processor having a software program for adjusting the local clock frequency after the threshold condition occurs.

8. (Previously Amended) A system according to Claim 7, wherein the threshold condition is a function of the difference between the local clock value and the program clock value.

9. (Original) A system according to Claim 7, wherein the processor is not used to adjust the local clock frequency until the threshold condition occurs.

10. (Original) A system according to Claim 7, said hardware includes:

means for monitoring for the occurrence of the threshold condition; and

means for transmitting a signal to the processor when the threshold

condition occurs.

11. (Cancelled)

12. (Cancelled)

13. (Previously Amended) A system for synchronizing the frequency of a local clock of a digital data decoder with the frequency of a program clock, comprising:

means for determining if there is any difference between the local and

program clock frequencies; and

means for adjusting the frequency at which the local clock oscillates, when there is a difference between the local clock and the program clock frequencies, so that said difference approaches zero, wherein the means for adjusting includes

- i) hardware on the decoder for adjusting the local clock frequency until a threshold condition occurs, and
- ii) a processor on the decoder and having a software program for adjusting the local clock frequency after the threshold condition occurs.

14. (Currently Amended) A system according to Claim 13, wherein the local clock has a local clock value and the program clock has a program clock value, and the threshold condition is a function of the difference between the local clock value and the program clock value.

FI
CA
15. (Previously Added) A system according to Claim 13, wherein said hardware includes

means for monitoring for the occurrences of the threshold condition; and

means for transmitting a signal to the processor when the threshold condition occurs.--